

MOTICAM Series

# MOTICAM 4000X





MOTICAM Series

## MOTICAM 4000X

<b>Sensor type</b>	CMOS
<b>Sensor size</b>	1/2.8"
<b>Light sensitive area</b>	Diagonal 6.4mm
<b>Capture resolution</b>	8MP (3864x2228 pixels)
<b>Pixel size</b>	1.45x1.45µm
<b>Scan mode</b>	Progressive
<b>Shutter Mode</b>	Rolling shutter
<b>Interface and key functions</b>	
<b>USB 2.0</b>	Female Type-A Port – Computer, Mouse Support
<b>USB 3.0</b>	Female Type-A Port – Computer, UVC
<b>HDMI</b>	3840x2160@30HZ
<b>Network port</b>	100Mbps RJ45 (no indicator)
<b>SD card</b>	SD2.0, SD3.0 support (SDHC, SDXC card support)
<b>Power button</b>	On/Off switch
<b>WIFI reset button</b>	Long press to reset
<b>LED indicator</b>	Red light: power indicator, always on when power on standby Green light: Power on indicator, blinking when power on, always on after power on
<b>Video encoding</b>	
<b>WIN/MAC</b>	MJPG/H264
<b>USB 2.0 and USB 3.0</b>	3840x2160/30fps 1920x1080/30fps 960x540/30fps

\*Frames per second under optimal lighting conditions and in compliance with computer technical requirements.

